Representation of floating point numbers in IEEE 754 standard:

single precision



double precision



MIPS assembly language

Category	Instruction	Example		Meaning	Comments
Arithmetic	add	add	$s1,$s2,$s3	$s1 = $s2 + $s3	Three operands; overflow detected
	subtract	sub	$s1,$s2,$s3	$s1 = $s2 – $s3	Three operands; overflow detected
	add immediate	addi	$s1,$s2,100	$s1 = $s2 + $s3	+ constant; overflow detected
	add unsigned	addu	$s1,$s2,$s3	$s1 = $s2 + $s3	Three operands; overflow undetected
	subtract unsigned	subu	$s1,$s2,$s3	$s1 = $s2 – $s3	Three operands; overflow undetected
	add immediate unsigned	addiu	$s1,$s2,100	$s1 = $s2 + $s3	+ constant; overflow undetected
	move from coprocessor register	mfc0	$s1,$epc	$s1 = $epc	Used to copy Exception PC plus other special registers
	multiply	mult	$s2,$s3	Hi, Lo = $s2 × $s3	64-bit signed product in Hi, Lo
	multiply unsigned	multu	$s2,$s3	Hi, Lo = $s2 × $s3	64-bit unsigned product in Hi, Lo
	divide	div	$s2,$s3	Lo = $s2 / $s3, Hi = $s2 mod $s3	Lo = quotient, Hi = remainder
	divide unsigned	divu	$s2,$s3	Lo = $s2 / $s3, Hi = $s2 mod $s3	Unsigned quotient and remainder
	move from Hi	mfhi	$s1	$s1 = Hi	Used to get copy of Hi
	move from Lo	mflo	$s1	$s1 = Lo	Used to get copy of Lo
Logical	and	and	$s1,$s2,$s3	$s1 = $s2 & $s3	Three reg. operands; logical AND
	or	or	$s1,$s2,$s3	$s1 = $s2 | $s3	Three reg. operands; logical OR
	and immediate	andi	$s1,$s2,100	$s1 = $s2 & 100	Logical AND reg, constant
	or immediate	ori	$s1,$s2,100	$s1 = $s2 | 100	Logical OR reg, constant
	shift left logical	sll	$s1,$s2,10	$s1 = $s2 << 10	Shift left by constant
	shift right logical	srl	$s1,$s2,10	$s1 = $s2 >> 10	Shift right by constant
Data transfer	load word	lw	$s1,100($s2)	$s1 = Memory[$s2+100]	Word from memory to register
	store word	sw	$s1,100($s2)	Memory[$s2 + 100] = $s1	Word from register to memory
	load byte unsigned	lbu	$s1,100($s2)	$s1 = Memory[$s2 + 100]	Byte from memory to register
	store byte	sb	$s1,100($s2)	Memory[$s2 + 100] = $s1	Byte from register to memory
	load upper immediate	lui	$s1,100	$s1 = 100 * 2^{16}	Loads constant in upper 16 bits
Conditional branch	branch on equal	beq	$s1,$s2,25	if ($s1 == $s2) go to PC + 4 + 100	Equal test; PC-relative branch
	branch on not equal	bne	$s1,$s2,25	if ($s1 != $s2) go to PC + 4 + 100	Not equal test; PC-relative
	set on less than	slt	$s1,$s2,$s3	if ($s2 < $s3) $s1 = 1; else $s1 = 0	Compare less than; two's complement
	set less than immediate	slti	$s1,$s2,100	if ($s2 < 100) $s1 = 1; else $s1=0	Compare < constant; two's complement
	set less than unsigned	sltu	$s1,$s2,$s3	if ($s2 < $s3) $s1 = 1; else $s1=0	Compare less than; natural numbers
	set less than immediate unsigned	sltiu	$s1,$s2,100	if ($s2 < 100) $s1 = 1; else $s1 = 0	Compare < constant; natural numbers
Unconditional jump	jump	j	2500	go to 10000	Jump to target address
	jump register	jr	$ra	go to $ra	For switch, procedure return
	jump and link	jal	2500	$ra = PC + 4; go to 10000	For procedure call

Main MIPS assembly language instruction set. The floating-point instructions are shown in Figure 4.47 on page 291. Appendix A gives the full MIPS assembly language instruction set.

MIPS machine language

Name	Format	Example						Comments
		6 bits	5 bits	5 bits	5 bits	5 bits	6 bits	
add	R	0	2	3	1	0	32	add $1,$2,$3
sub	R	0	2	3	1	0	34	sub $1,$2,$3
addi	I	8	2	1	100			addi $1,$2,100
addu	R	0	2	3	1	0	33	addu $1,$2,$3
subu	R	0	2	3	1	0	35	subu $1,$2,$3
addiu	I	9	2	1	100			addiu $1,$2,100
mfc0	R	16	0	1	14	0	0	mfc0 $1,$epc
mult	R	0	2	3	0	0	24	mult $2,$3
multu	R	0	2	3	0	0	25	multu $2,$3
div	R	0	2	3	0	0	26	div $2,$3
divu	R	0	2	3	0	0	27	divu $2,$3
mfhi	R	0	0	0	1	0	16	mfhi $1
mflo	R	0	0	0	1	0	18	mflo $1
and	R	0	2	3	1	0	36	and $1,$2,$3
or	R	0	2	3	1	0	37	or $1,$2,$3
andi	I	12	2	1	100			andi $1,$2,100
ori	I	13	2	1	100			ori $1,$2,100
sll	R	0	0	2	1	10	0	sll $1,$2,10
srl	R	0	0	2	1	10	2	srl $1,$2,10
lw	I	35	2	1	100			lw $1,100($2)
sw	I	43	2	1	100			sw $1,100($2)
lui	I	15	0	1	100			lui $1,100
beq	I	4	1	2	25			beq $1,$2,100
bne	I	5	1	2	25			bne $1,$2,100
slt	R	0	2	3	1	0	42	slt $1,$2,$3
slti	I	10	2	1	100			slti $1,$2,100
sltu	R	0	2	3	1	0	43	sltu $1,$2,$3
sltiu	I	11	2	1	100			sltiu $1,$2,100
j	J	2	2500					j 10000
jr	R	0	31	0	0	0	8	jr $31
jal	J	3	2500					jal 10000

MIPS instruction formats

Name	Fields						Comments
Field size	6 bits	5 bits	5 bits	5 bits	5 bits	6 bits	All MIPS instructions 32 bits
R-format	op	rs	rt	rd	shamt	funct	Arithmetic instruction format
I-format	op	rs	rt	address/immediate			Transfer, branch, imm. format
J-format	op	target address					Jump instruction format

Main MIPS machine language. Formats and examples are shown, with values in each field: op and funct fields form the opcode (each 6 bits), rs field gives a source register (5 bits), rt is also normally a source register (5 bits), rd is the destination register (5 bits), and shamt supplies the shift amount (5 bits). The field values are all in decimal. Floating-point machine language instructions are shown in Figure 4.47 on page 291. Appendix A gives the full MIPS machine language.