# Announcements

- Homework 2 Due on Friday

# Last Time

- Shortest Paths in Graph with Negative Edge Weights
  - Negative weight cycles
    - might mean no shortest paths
  - `Bellman-Ford`
    - Computes shortest path length with ≤ k edges for various k
    - If no negative weight cycles, take k = |V|-1 to get correct distances.

# Algorithm

```
Bellman-Ford(G,s,ℓ)
  dist_0(v) ← ∞ for all v
    //cant reach
  dist_0(s) ← 0
  For k = 1 to n
    For w ∈ V
      dist_k(w)←min(dist_k-1(v)+ℓ(v,w))
    dist_k(s) ← min(dist_k(s),0)
      // s has the trivial path
```

# Result

**Proposition:** If $n \geq |V|-1$ and if G has no negative weight cycles, then for all v,

$$dist(v) = dist_n(v).$$

`Bellman-Ford` computes shortest paths if no negative weight cycles in time $O(|V||E|)$.

# Today

- Detecting Negative Weight Cycles.
- Shortest Paths in DAGs.
- Divide & Conquer

# Detecting Negative Cycles

*If* there are no negative weight cycles, Bellman-Ford computes shortest paths (and they might not exist otherwise).

How do we know whether or not there are any?

# Cycle Detection

**Proposition:** For any $n \geq |V| - 1$, there are no negative weight cycles reachable from s if and only if for every $v \in V$

$$dist_n(v) = dist_{n+1}(v)$$

- Detect by running one more round of Bellman-Ford.
- Need to see if *any* v's distance changes.

# Proof of “Only If”

- Suppose no negative weight cycles.
- For any $n \geq |V| - 1$, $dist_n(v) = dist(v)$.
- So

$$dist_n(v) = dist(v) = dist_{n+1}(v)$$

# Proof of "If"

Suppose $\text{dist}_n(v) = \text{dist}_{n+1}(v)$ for all v.

$$\begin{aligned}\text{dist}_{n+2}(w) &= \min_{(v,w)\in E}(\text{dist}_{n+1}(v) + \ell(v,w)) \\ &= \min_{(v,w)\in E}(\text{dist}_{n}(v) + \ell(v,w)) \\ &= \text{dist}_{n+1}(w).\end{aligned}$$

So

$$\text{dist}_n(v) = \text{dist}_{n+1}(v) = \text{dist}_{n+2}(v) = \text{dist}_{n+3}(v) = \ldots$$

But if there were a negative weight cycle, distances would decrease eventually.

# Alternative Proof

- Assume $dist_n(v) = dist_{n+1}(v) = d(v)$ for all v.
- $d(w) = \min(d(v)+\ell(v,w))$.
  - $d(w) \leq d(v)+\ell(v,w)$ for all $(v,w) \in E$
  - $\ell(v,w) \geq d(w) - d(v)$
- Given cycle $v_1,v_2,v_3,\ldots,v_m$ total length of cycle is

$$\begin{aligned} & \ell(v_1, v_2) + \ell(v_2, v_3) + \ldots + \ell(v_m, v_1) \\ \geq\ & -d(v_1) + d(v_2) - d(v_2) + d(v_3) - \ldots - d(v_m) + d(v_1) = 0. \end{aligned}$$

# Potential Function

- Let $\ell'(v,w) = \ell(v,w) - d(v) + d(w) \geq 0$
  - Imagine somebody lending you d(w) when you arrive at w, but having to pay it back when you leave.
- For any s-t path P, $s, v_1, v_2, \ldots, t$

$$\begin{aligned}\ell'(P) &= \ell'(s,v_1) + \ell'(v_1,v_2) + \ldots + \ell'(v_m,t) \\ &= \ell(s,v_1) + \ell(v_1,v_2) + \ldots + \ell(v_m,t) \\ &\quad - d(s) + d(v_1) - d(v_1) + d(v_2) + \ldots - d(v_m) + d(t) \\ &= \ell(P) - d(s) + d(t).\end{aligned}$$

- Shortest paths same. Non-negative edges.

# Shortest Paths in DAGs

We saw that shortest paths is harder when we needed to deal with negative weight cycles. For general graphs, we needed to use Bellman-Ford, which is much slower than our other algorithms.

One way to avoid this was to make edge weights non-negative. In this case, we could use Dijkstra.

Another way to get rid of negative weight cycles, is to get rid of cycles. If G is a DAG, there are better algorithms.

# Fundamental Shortest Paths Formula

$$\text{For } w \neq s,$$
$$\text{dist}(w) = \min_{(v,w) \in E} \text{dist}(v) + \ell(v, w).$$

Hard to apply in general because there's no order to solve equations in.

DAG gives topological order!

# Algorithm

Runtime
O(|V|+|E|)


```
ShortestPathsInDAGs(G,s,ℓ)
  TopologicalSort(G)
  For w ∈ V in topological order
    If w = s, dist(w) ← 0
    Else
     dist(w)←min(dist(v)+ℓ(v,w))
\\ dist(v) for all upstream v
  already computed
```

O(|V+|E|)

O(|V|) total

O(|E|) total

# Example



# Shortest Path Algorithms Summary

Unit Weights: `Breadth First Search`
O(|V|+|E|)

Non-negative Weights: `Dijkstra`
O(|V|log|V|+|E|)

Arbitrary Weights: `Bellman-Ford` O(|V||E|)

Arbitrary Weights, graph is a DAG:
`Shortest-Paths-In-DAGs` O(|V|+|E|)

# Divide & Conquer (Ch 2)

- General Technique
- Master Theorem
- Karatsuba Multiplication
- Strassen's Algorithm
- Merge Sort
- Order Statistics
- Binary Search
- Closest Pair of Points

# Divide and Conquer

This is the first of our three major algorithmic techniques.

1. Break problem into pieces
2. Solve pieces recursively
3. Recombine pieces to get answer

# Example: Integer Multiplication

**Problem:** Given two n-bit numbers find their product.

**Naïve Algorithm:** Schoolboy multiplication. The binary version of the technique that you probably learned in elementary school.

# Schoolboy Multiplication

$$
\begin{array}{rl}
 & a_1 \quad a_2 \quad a_3 \quad \ldots a_{n-1} \quad a_n \\
\times & b_1 \quad b_2 \quad b_3 \quad \ldots b_{n-1} \quad b_n \\
\hline
 & a_1b_1 \; a_2b_1 \; a_3b_1 \ldots a_{n-1}b_1 \; a_nb_1 \\
 & a_1b_2 \; a_2b_2 \; a_3b_2 \; a_4b_2 \ldots a_nb_2 \; 0 \\
 & \ldots \quad \ldots \quad \ldots \quad \ldots \quad \ldots \; \ldots \quad \ldots \\
+ & a_1b_n \; a_2b_n \; a_3b_n \ldots \; a_nb_n \; 0 \quad 0 \quad \ldots 0 \quad 0 \\
\hline
\end{array}
$$

ANSWER

# Question: Runtime

What is the asymptotic runtime of the schoolboy algorithm?

A) $O(n)$

B) $O(n \log(n))$

C) $O(n^2)$

D) $O(n^3)$

E) $O(2^n)$

Need to write down $O(n^2)$ bits of numbers to add. Addition can be done in linear time.

# Two Digit Multiplication

```
              a        b
          x   c        d
          ----------
              ad      bd
    +  ac     bc       0
    ----------------------
       ac  ad+bc      bd
```

# Two-Digit Multiplication

(ab) ·(cd) = [ac][bc+ad][bd]


Requires 4 one-digit multiplications and one addition.

**Trick:** Compute ac, bd, (a+b)(c+d).
Note that bc+ad = (a+b)(c+d) – ac – bd.

Requires 3 one-digit multiplications and 4 addition/subtractions.

How can we apply this to larger problems?

# Larger Base


A
B
$a_1$ $a_2$ $a_3 \ldots a_{n/2}$ $a_{n/2+1} \ldots a_n$
C
D
x $b_1$ $b_2$ $b_3 \ldots b_{n/2}$ $b_{n/2+1} \ldots b_n$
AC
AD+BC
BD

# Formally

Want to multiply N and M:

1. Let $X \approx \sqrt{(N+M)}$ be a power of 2.
2. Write $N = AX+B$, $M = CX+D$
   - This can be done by just taking the high and low bits.
3. $N \cdot M = AC \cdot X^2+(AD+BC)X+BD$
   $= AC \cdot X^2+[(A+B)(C+D)-AC-BD]X + BD$
   - The multiplications by X are just bit shifts.

# Improved Multiplication

```
ImprovedMult(N,M)
   Let X be a power of 2^⌊log(N+M)/2⌋
   Write N = AX + B, M = CX + D
   P1 ← Product(A,C)
   P2 ← Product(B,D)
   P3 ← Product(A+B,C+D)
   Return P1X^2 + [P3-P1-P2]X + P3
```

O(n)

O(n²)

O(n)

Runtime: $O(n^2)$. No asymptotic improvement!

# More Detailed Analysis

This algorithm shows no *asymptotic* improvement, but it is better.

To analyze this, lets suppose that computing the product of two n-bit numbers using the schoolboy algorithm takes $n^2$ time.

# Improved Multiplication

```
ImprovedMult(N,M)
   Let X be a power of 2^⌊log(N+M)/2⌋
   Write N = AX + B, M = CX + D
   P1 ← Product(A,C)
   P2 ← Product(B,D)
   P3 ← Product(A+B,C+D)
   Return P1X^2 + [P3-P1-P2]X + P3
```

O(n)

3(n/2)²

O(n)

Runtime: $(3/4)n^2+O(n)$.

Better than $n^2$!

# Further Improvements

So this trick does help. Saving a multiplication at the cost of a few extra additions is a big deal, when multiplications are $O(n^2)$ and additions are $O(n)$.

Can we do better?

Yes. Our algorithm is still using schoolboy multiplication to do the smaller multiplications. We can instead use our faster algorithm.

# Further Improvement

```
KaratsubaMult(N,M)
   If N+M<99, Return Product(N,M)
   Let X be a power of 2^⌊log(N+M)/2⌋
   Write N = AX + B, M = CX + D

   P1 ← Product(A,C)
   P1 ← KaratsubaMult(A,C)
   P2 ← Product(B,D)
   P2 ← KaratsubaMult(B,D)
   P3 ← Product(A+B,C+D)
   P3 ← KaratsubaMult(A+B,C+D)
   Return P1X^2 + [P3-P1-P2]X + P3
```

O(n)

???

O(n)